



Famiwell

Do right things to get dream life

www.famiwell.com

| Model | HD20D2V100 | HD20D2F200 | HD20D2S200 | HD20D2SH200 | HD20D2K500 | HD20D2S500 |
|---------------------|--------------------------------|--------------------|--------------------|--------------------|--------------------|--------------------|
| Image Sensor | 1/4" CMOS sensor | 1/2.7" CMOS Sensor | 1/2.8" CMOS Sensor | 1/2.8" CMOS Sensor | 1/2.7" CMOS Sensor | 1/2.9" CMOS Sensor |
| Sensor Brand | OV | Silicon | Sony | Sony | Silicon | OV |
| HD Video output | AHD/CVI/TVI | AHD/CVI/TVI | AHD/CVI/TVI | AHD/CVI/TVI | AHD/CVI/TVI | AHD/CVI/TVI |
| Image Resolution | 720P | 1080P | 1080P | 1080P | 5MP | 5MP |
| OSD Menu | No | Yes | Yes | Yes | Yes | Yes |
| WDR | No | DWDR | DWDR | DWDR | DWDR | DWDR |
| Effective Pixels | 1305(H)x977(V) | 1930(H) × 1088(V) | | | 2592(H) × 1944(V) | |
| TV System | PAL/NTSC | | | | | |
| S/N Ratio | More than 62 dB | | | | | |
| Scanning System | Progressive Scan | | | | | |
| Synchronization | Internal | | | | | |
| Noise Reduction | DNR | DNR | DNR | 3D NR | DNR | DNR |
| White Balance | Auto/Manual | | | | | |
| Gain Control | Auto | | | | | |
| Picture Adjustment | Yes | | | | | |
| IR Features | | | | | | |
| Infrared LED | 14μX12PCS | | | | | |
| Max. IR LEDs Length | 20m, Smart IR | | | | | |
| IR Status | Under 10 Lux by CDS | | | | | |
| IR power on | CDS Auto Control | | | | | |
| Day/Night | IR cut filter with auto switch | | | | | |
| Lens | | | | | | |
| Focal length | 3.6mm (2.8mm & 3.6mm optional) | | | | | |
| Lens Type | Fixed | | | | | |
| Mount Type | M12 | | | | | |
| General | | | | | | |
| Housing | Plastic | | | | | |
| Bracket | Yes | | | | | |
| Power Supply | DC12V,500mA | | | | | |
| Working Environment | -10°C~+50°C / 20%~95%RH | | | | | |
| Storage Temperature | -20°C ~ +60°C RH95% Max | | | | | |
| Dimensions(W×H×D) | ∅ 94 x 69(H) mm | | | | | |
| Weight | 350g | | | | | |